

Arcade Legends Computer 2 (White desktop style case)
 CMOS Setup Utility – Copyright © 1984-2001 Award Software

- | | | |
|--|--|--|
| <ul style="list-style-type: none"> > Standard CMOS Features > Advanced BIOS Features > Advanced Chipset Features > Intergrated Peripherals > Power Management Setup > PNP / PCI Configurations > Frequency / Voltage Control | | <ul style="list-style-type: none"> Load Fail-Safe Defaults Load Optimized Defaults Set Supervisor Password Set User Password Save & Exit Setup Exit Without Saving |
|--|--|--|

<p style="text-align: center;">Standard CMOS Features</p> <p>Date – Set to current date Time – Set to current time</p> <ul style="list-style-type: none"> > IDE Primary Master > IDE Primary Slave > IDE Secondary Master > IDE Secondary Slave <p>Drive A None Drive B None Video EGA / VGA Halt On No Errors</p> <hr/> <p style="text-align: center;">Advanced Chipset Features</p> <p>SDRAM CAS Latency Time 3 SDRAM Cycle Time Trans/Trc Auto SDRAM RAS-to-CAS Delay Auto SDRAM RAS Precharge Time Auto System BIOS Cacheable Disabled Video ROM Cacheable Disabled CPU Latency Timer Disabled Delayed Transaction Enabled On-Chip Video Window Size 64MB</p> <p>.....</p> <p>CAS# Latency 3 Paging Mode Control Open RAS-to-CAS Override byCAS# LT RAS# Timing Fast RAS Precharge Timing Fast</p>		<p style="text-align: center;">Advanced BIOS Features</p> <p>Virus Warning Disable CPU Internal Cache Enabled External Cache Enabled CPU L2 Cache ECC Check Enabled Processor Number Feature Enabled Quick Power On Self Test Enable First Boot Device CDROM Second Boot Device HDD-0 Third Boot Device LS120 Boot Other Device Enabled Swap Floppy Drive Disabled Boot Up Floppy Seek Disabled Boot Up Numlock Status ON Gate A20 Options Fast Typematic Rate Setting Disable</p> <p>.....</p> <p>.....</p> <p>Security Option Setup OS Select for DRAM>64MB Non-OS2 Report NoFDD For Win95 No Small Logo(EPA) Show Disabled</p> <p><<< The Advanced Chipset Features menu is shown for reference ONLY and is automatically configured by BIOS. If you change anything on this menu from the the default settings you can destroy the memory board. Leave it alone.</p>
--	--	---

Integrated Peripherals

OnChip Primary PCI IDE	Enabled
OnChip Secondary PCI IDE	Enabled
IDE Primary Master PIO	Auto
IDE Primary Slave PIO	Auto
IDE Secondary Master PIO	Auto
IDE Secondary Slave PIO	Auto
IDE Primary Master UDMA	Auto
IDE Primary Slave UDMA	Auto
IDE Secondary Master UDMA	Auto
IDE Secondary Slave UDMA	Auto
USB Controller	Enabled
USB Keyboard Support	Disabled
AC97 Audio	Auto
AC97 Modem	Auto
IDE HDD Block Mode	Enabled
Onboard FDC Controller	Disabled
Onboard Serial Port 1	3F8/IRQ4
Onboard Serial Port 2	Disabled
Onboard Parallel Port	378/IRQ7
Parallel Port Mode	SPP
PWRON After PWR-Fail	ON
Game Port Address	201
Midi Port Address	330
Midi Port IRQ	10

Save and exit setup

- In the event of battery replacement we recommend leaving the battery out for a minimum of 30 minutes before replacing it with a new one.
- This Motherboard is found mostly in White desktop style cases.
- This computer uses battery number CR-2032.
- Some early production motherboards REQUIRE you to set the current date and time or an error with no description is generated on the boot screen and WILL halt loading of the game software and continue showing 'snow' on the screen. If in doubt set the date and time.
- Once these changes are made the computer will restart on it's own and should display a logo of some type, then most VGA monitors will 'go to sleep' or display an 'out of range' message if your machine already has the game software installed on the hard drive.
This is completely normal and expected if the configuration is correct.